

SMART LIGHTING > Lighting control by Nexta Tech > Receivers Driver control 0-1/10V, dali, Push dim or phase cut

15TOP0110

Control unit interface TOP-0110 for drivers 0-1/10V 2000W

May 19th, 2024, 00:41





DESCRIPTION

Interface control unit with dimmer function for wireless control via 433.92MHZ radio or with standard push button cable of devices with 0-10V or 1-10V input. Power 110-240Vac. Output 0-10V / 1-10V Maximum power 2000W (240Vac) The programming by display is intuitive and fast while its small dimensions allow for installation in the false ceiling or junction boxes.

PRICE

Lot	P.V.P. excluding VAT
1	86,68€
10	82,55€

Continued on next page >>



SMART LIGHTING > Lighting control by Nexta Tech > Receivers Driver control 0-1/10V, dali, Push dim or phase cut

15TOP0110

Control unit interface TOP-0110 for drivers 0-1/10V 2000W

TECHNICAL SPECIFICATIONS

SYMBOLS CERTIFICADOS







Weight: 227 Grams

NOTES

Receiver for RF regulation or cable of devices with input 0-1 / 10V max 2000W

OTHER FEATURES

Length (mm): 174 Width (mm): 46

High (mm): 35 Voltage In (Vac): 110~240 Power (W): 2000 Ingress Protection: IP20

DOCUMENTS

Quick start quide

Mounting instructions

CE