

SMART LIGHTING > Lighting control by Nexta Tech > Receivers
Driver control 0-1/10V, dali, Push dim or phase cut

15TOP0110ONE

Control unit interface TOP-0110/ONE for drivers 0-1/10V 2000W

May 03rd, 2024, 10:02



DESCRIPTION

Receiver control unit for the control of Led driver 230Vac dimmable 0 / 1-10V. Selectable functions: 1 ON-OFF 2. 0-10V output 3. 1-10V output. It is powered at 230Vac. Maximum 2000W. With four forms of command: 1. Push wiring (1 input) 2. With RF controls 3. Via mobile control with WI-FI with iOS and Android App. 4 Voice control compatible Google Home and Amazon Alexa.

PRICE

	Lot	P.V.P. excluding VAT
	1	88,81€
	10	84,58€



Continued on next page >>

SMART LIGHTING > Lighting control by Nexta Tech > Receivers
Driver control 0-1/10V, dali, Push dim or phase cut

15TOP0110ONE

Control unit interface TOP-0110/ONE for drivers 0-1/10V 2000W

TECHNICAL SPECIFICATIONS

SYMBOLS



Weight: 190 Grams

CERTIFICADOS



NOTES

For control of 0 / 1-10V Drivers

OTHER FEATURES

Length (mm): 176

Width (mm): 46

High (mm): 35

Voltage In (Vac): 230

Power (W): 2000